



# Veil80

Mechanical Keyboard

Quick Start Guide

## **Fn Shortcut Keys:**

**Fn + ↑**

LED Brightness Up

**Fn + ↓**

LED Brightness Down

**Fn + →**

Speed up lightmode

**Fn + ←**

Slow down lightmode

**Fn + Right Shift**

Toggle Power Saving Mode (all lights out)

**Fn + Esc**

Switch from Light Mode / Single Color Mode

**Fn + Backspace**

Toggle Backlights On / Off

**Fn + Enter**

Change Backlight Color

**Fn + | \**

Change Lighting Modes (14 modes)

**Fn + M**

Hold down for 2 sec, Spacebar will blink twice to go into MAC mode

Spacebar will blink once to goto Windows mode

**Fn + F**

On Mac Mode, switch multimedia key to standard key for the F keys

**Fn + I**

Insert

**Fn + C**

Open My Computer

**Fn + P**

Printscreen

**Fn + L**

Open Browser

## **Fn Shortcut Keys:**

**Fn + PgUp**

Home

**Fn + PgDn**

End

**Fn + Win key**

Win key lock

**Fn + 5**

Switch to wired mode

**Fn + F10**

Toggle Mute

**Fn + F11**

Volume Down

**Fn + F12**

Volume Up


**Restore Default**

Hold down 3 sec (ESC, Left CTRL, F12, Right arrow)

**Connectivity switch:** ( located at the back of the keyboard along with USB Dongle )

Toggle On/Off for Wireless mode / Wired mode.

**Wireless Connection:** ( Connect/Store up to 3 BT Devices + 2.4g mode )

<b>BT 1</b>	<b>Fn + 1</b>	<b>Long press ( 3 sec )</b> for pairing mode between the BT device. Corresponding number Key will blink fast when discoverable. Key will stop blinking when paired.
<b>BT 2</b>	<b>Fn + 2</b>	
<b>BT 3</b>	<b>Fn + 3</b>	<b>Single press</b> to connect/disconnect to paired device. Corresponding number key will stop blinking when connection is established.
 <b>4</b>	<b>Fn + 4</b>	<b>Single press</b> to switch to 2.4g mode and connect the USB Dongle. Corresponding number key will stop blinking when connection is established.

**Lighting Sleep/Time out:** ( 2 min or No time out )

Fn + Tab key to change the Sleep/Time out duration setting

The Caps lock key will serve as an indicator and will blink once for 2min, twice for No time out.

**Battery Indicator:** F12 Key light color

Breathing Red light is Low Battery. Breathing Green light is Charging. Light will go back to normal when full charged.

**TECWARE**

[www.tecware.co](http://www.tecware.co)